

## DMA6124



The DMA6124 multi-function matrix public address system is a newly designed and highly integrated audio matrix host system. This new system not only features an 8×6 signal matrix but also includes multimedia playback capabilities. It incorporates a six-channel output design that supports 100V constant voltage output. Additionally, it supports the DMA60M remote paging microphone with a glass panel touch button design and the DMA60W Bluetooth touch panel, both as expansion peripherals. The multi-function matrix PA hosts DMA6112 and DMA6124 are specified at 6×120W and 6×240W, respectively, both designed with a 2U chassis. The high degree of integration in these devices helps save space and reduce wiring complexity. They come with a comprehensive set of logical interfaces and a well-defined priority system, making them suitable for most small to medium-sized broadcast system applications. Additionally, they can be integrated with other systems for enhanced functionality.

|                          |                     |
|--------------------------|---------------------|
| Manufacturer Name:       | DSPPA               |
| Model:                   | DMA6124             |
| Part Number:             |                     |
| Zones Numbers            | 6                   |
| Power (100V) per channel | 240                 |
| Microphone Inputs        | 2                   |
| Music Input Source       | 4                   |
| Output Voltage           | 100V, 4Ω / 16Ω, 70V |
| Rack Mount               | Yes                 |
| Application              | Installation        |
|                          | Installation        |
| Guarantee                | 2 Years Guarantee   |

Retail Price  
**1.306,00€ \***

\*VAT Included in Retail Price 24%

Code: E026383-(AA)

Part Number:

Price for: pcs

6 Channels Digital Audio Matrix Amplifier  
with Remote Control